

Leading the way in security

Scantronic

9751 HYBRID ALARM SYSTEM

CONTROL PANELS



9954



715R



9955



725R



735R



726R



719R



9928



934EUR-50

The Scantronic 9751 control panel is a fully programmable, 8 zone alarm panel, which can be expanded to 24 zones to protect up to 24 potentially vulnerable areas of a building.

The system can be expanded using hardwired or Class VI 868 MHz narrow band wirefree technology ensuring flexibility whatever the installation requirement. The wirefree expander eliminates the need for complex wiring between devices, causing a minimum of disruption to décor.

The 9751 is ideally suited to the domestic market and small commercial market. Designed to offer maximum flexibility and ease of use, up to 4 remote keypads can be housed in separate locations of the building. Exceptionally easy to operate using large backlit A, B and C buttons you can have level setting options of the whole premises, ground floor only or any other plan that suits your particular setting requirements.

Upload and download technology is available using a Windows based program, which greatly reduces maintenance time by allowing the engineer to diagnose and program the system remotely. Additionally, the 9751 has a 250 event log which is downloadable.

There is a built-in 300 baud modem for communications and secondary communications outputs for other devices.

9751

HYBRID ALARM SYSTEM

TECHNICAL SPECIFICATION

Zones	8 fully programmable, expandable to 24 (CC, 4 wire, with global tamper, or 2 Wire FSL)
Zone Attributes	Each zone can be programmed as one of the following types - personal attack, fire, normal alarm, final exit, 24 hour, entry route, not used, shock analyser (zones 1-4 only), technical alarm, key-switch (fixed & momentary options) attributes of chime, soak test, double knock, omit allowed
Panel	9751 Blank end station control panel and 9930 LCD keypad packaged as a kit
Keypads	Accepts up to 4 9930 LCD remote keypads and one 9928 key switch interface
Proximity Reader	A plug-on module that turns a Scantronic keypad into a combined keypad and proximity reader - compatible with 9930EUR-50 and 931EUR-50 keypads
Display	9930, Full feature LCD display with plain text up to 16 characters
Level Setting	A = Full Set, B & C as Part set
Event Log	250 event log with date and time stamped, viewed or downloaded
Expansion	Via a choice of 2 x 8 zones hardwired or 2 x 8 zones 868MHz "Class VI" narrow band radio expansion or 1 of each
Compliance	EN50131-1 Grade 2 and current BS4737 Part 1 for remote signalled systems, ACPO 2000, DD243:2002, DD244 & BS6799 "Class VI" radio
Keyswitch	Via 9928 interface or key-switch zone type, full = A, part = B setting/unsetting, disarm and reset
Codes	16 x 4 digit user access codes, 1 duress code, 1 engineer code
Internal Sounder	Accepts up to 2 x 16 ohm internal sounders, exit/entry tones via internal sounder with electronic volume control
Outputs	Outputs 1, 2 & 3 are open collector. All outputs programmable as bell, exit/entry follow, armed lamp, set latch, shock reset, walk test (LED enable), ready lamp, 24 hour alarm, strobe, smoke reset, strobe when setting, siren test, pulsed set, pulsed unset, confirm, set complete, unset complete
Remote Communications	Multi-format alarm reporting via a built in communicator, 8 channel fast format, SIA I, II or III or Contact ID
Modem	Built in CCITT V21 - 300 BAUD 1/2 duplex
Downloader	Remote downloader facilities for programming, diagnostics and remote control using Cooper Security Multi-Product downloader software, Windows based, Secure Callback (with dynamic third callback number), answerphone defeat option and unattended mode, manual call out
Remote Diagnostics	Designed to conform to the BSIA Remote Service COP, Remote tests include read Zone's resistances (panel & expander), zone activity, RFX signal strength, PSU voltages, current, battery charge and system on load current, remotely trigger output tests, communications test, operate system with a virtual keypad
Servicing	Conforms to EN50131-6 Type A power supply for Grade 2 systems
Power Supply	Stand by battery 12 volt, 7Ah rechargeable lead acid, gel type
Battery	1 Amp
System Power Supply	500 mA @ 13.7 volts
Aux DC Power for Detectors	400 mA @ 13.7 volts
Dimensions	Control panel (H x W x D) = 240 x 240 x 90mm, keypad (H x W x D) = 120 x 170 x 27mm
Weight	Control panel = 3.3kg, keypad = 260g
Temperature Range	-10°C to 55°C
Secondary Communications	Any type of wire in secondary communications device via 8 Fully Programmable Secondary Communications Outputs
Outputs	9928EUR-00 Key Switch Interface
Scantronic Compatible Equipment	9930EUR-00 LCD Keypad 9954EUR-00 Hardwired 8 Zone Expander (FSL or CC, with common tamper, diagnostics ready). 9955EUR-50 868MHz 'Class VI' Radio Expander (diagnostics ready) 735REUR-00 Door Contact Transmitter 715REUR-50 Wireless PIR Detector 719REUR-00 Smoke Detector c/w 868MHz Tx 725EUR-00 Telecommand Set/Unset + PA Tx. 726REUR-00 2 Button Hand Held PA 958EUR-00 Windows Downloader PC Software 934EUR-50 ScanProx module with 1 tag 9930EUR-50 Hybrid range keypad - ScanProx 931EUR-50 8136UK-50 Keypad - ScanProx compatible

Scantronic is a leading brand of Cooper Security Ltd, part of Cooper Industries, which employs over 30,000 people in 100 manufacturing sites around the world.

Scantronic manufactures security equipment for all types of commercial and domestic premises. The range is comprehensive, offering every type of solution from multizone hard-wired and wirefree systems, digital and voice communicators, detectors and social alarms. Installers trust us to deliver cost-effective products with the highest quality of field and support services, to ensure you receive the best and most reliable systems to secure your premises, and give you peace of mind.

Dealer Details

Scan 04/03